STATE OF NEW HAMPSHIRE

Department of Administrative Services

DIVISION OF PUBLIC WORKS DESIGN & CONSTRUCTION


ARPA - GREENFIELD STATE PARK UTILITIES UPGRADE PROJECT

973 FOREST ROAD, GREENFIELD, NH 03047

DPW Project #81204R Contract C


DEPARTMENT OF NATURAL & CULTURAL RESOURCES

FEDERAL AID PROJECT



HEB Engineers, Inc.


PO Box 440 2605 White Mtn. Hwy North Conway, NH 03860 p. 603-356-6936 f. 603-356-7715 e. egrenier@hebengineers.com



ELECTRICAL

Lee F. Carroll, PE

1 Madison Avenue
Gorham, NH 03581
p. 603-466-4065
f. 603-466-5062
e. lcarroll@ne.rr.com



11/16/2023

SHEET NUMBER

General Erosion—Control Requirements:

The primary intent of the erosion control requirements and the construction sequence is to stage the project in a manner that will minimize the potential for erosion and the potential negative effects associated therewith. The Engineer shall be contacted and the plan shall be amended if the intent is not being achieved.

1. Erosion control definitions:

"Strip topsoil": Excavate topsoil, screen, and stockpile.

"Seed(ing)": Adjust ph, apply fertilizer, sow the seed mixture, apply mulch (or erosion control matting), apply tackifier.

"Significant rainfall event": more than ¼—inch of rain.

- Install all erosion control measures prior to earthwork operation and maintain all erosion control measures and seeded embankments during construction. Erosion control shall be removed only upon the establishment of all vegetated areas.
- 3. All drainage structure inlets shall be protected using inlet protection or catch basin inserts.
- 4. Erosion control measures shall be implemented complying with the Best Management Practices (BMPs) of the "New Hampshire Stormwater Management Manual, Latest Edition, Post—Construction Best Management Practices Section & Design," by the New Hampshire Department of Environmental Services (NHDES), United States Department of Agriculture (USDA) SCS, and Rockingham County Conservation District, latest edition.
- 5. Do not disturb areas outside the limits of proposed work. Areas disturbed by the Contractor's operations shall be restored to their original condition at the Contractor's expense. All areas disturbed during construction not covered with buildings, structures or pavement shall receive four (4) inches of loam and seed.
- 6. The downhill side of all stockpiles shall be encircled with silt fence.
- 7. All ditches, swales, and other areas of concentrated flow shall be stabilized prior to directing flow to them. Inlet protection to be installed prior to directing flow to storm drains.
- 8. Before weekends, and if a significant rainfall event is anticipated during the construction of the cut/fill embankments, a temporary berm shall be constructed along the top of the fill embankments, and temporary slope drains (pipes) with temporary stone outlet aprons shall be installed at the base of the slopes.
- 9. The maximum time that any disturbed areas shall be left unstabilized shall be 14 days.
- 10. The smallest practical area shall be disturbed to complete the required construction, but no more than 5 acres at any one time.
- 11. All cut and fill slopes shall be seeded and mulched within 72 hours after their construction.
- 12. Lot disturbance, other than that shown on the approved plans, shall not commence until after the roadway and the associated drainage is complete and stable.
- 13. An area shall be considered stable if one of the following has occurred:
 - A. Base course gravels have been installed in areas to be paved;
 - B. A minimum of 85 percent vegetated growth has been established;
 C. A minimum of 3 inches of non—erosive material such as stone or riprap has been installed; or
- D. Erosion control blankets have been properly installed.
- 14. Throughout the construction period, all erosion—control measures shall be inspected at the end of each week and before anticipated significant rainfall events and repaired, if deficient. Extra attention shall be given to the critical areas listed separately.
- 15. All erosion control measures shall be inspected weekly, and after every 0.25 inches or greater rainfall within a
- 16. All roadways/parking areas and cut and fill slopes shall be stabilized within 72 hours of achieving finished grade.
- 17. Precaution shall be taken throughout the duration of construction activity to prevent, abate, and control the emission of fugitive dust, including but not limited to, wetting, covering, shielding, or vacuuming.
- 18. The project must meet the requirements and intent of RSA 430:53 and Agr 3800 relative to invasive species.
- 19. Temporary water diversions (swales, basins, etc.) must be used as necessary until areas are stabilized.
- 20. All construction dewatering shall be discharged to approved sedimentation basins.
- 21. Detention basins and swales shall be installed before rough grading at the site.

Critical Erosion Areas:

Temporary seeding and/or mulching shall be used to protect exposed critical areas during construction. The following areas are particularly susceptible to erosion and shall receive extra attention when being inspected and maintained:

- 1. Large cut and fill areas along road and driveways.
- 2. Areas not worked or not to be worked for 3 weeks.
- 3. Areas of concentrated flow such as ditches, swales, and toes of uphill facing slopes.
- 4. Stormwater ponds and level spreaders.

Temporary Seeding Notes:

- 1. Bedding: Remove stones and trash that will interfere with seeding the area. Where feasible, till the soil to a depth of about 3 inches to prepare a seedbed and mix fertilizer into the soil. The seedbed should be left in a firm and smooth condition. The last tillage operation should be performed across the slope wherever practical.
- 2. Fertilizers: Fertilizer should be uniformly spread over the area prior to being incorporated into the soil. A minimum of 300 pounds per acre (7 pounds per 1,000 square feet) of 10—10—10 fertilizer, or its equivalent, should be applied.
- 3. Where it is impracticable to incorporate fertilizer and seed into moist soil, the seeded area should be mulched to facilitate germination.
- 4. Seed Mixture: Use any of the following:

Species	Per Acre	Per 1,000 s.f.	Dates	Depth
Winter Rye	112 lbs.	2.5 lbs.	8 /15- 9/5	1 inch
Oats	80 lbs.	2.0 lbs.	Spring-5/15	1 inch
Annual Ryegrass	40 lbs.	1.0 lb.	4/15-9/15	¼ inch
Perennial Ryegrass	30 lbs.	0.7 lbs.	4/1-6/1 or	$\frac{1}{2}$ inch
, ,			8/15-9/15	-

5. Maintenance: If seeding fails to grow, it may need to be re—established to provide adequate erosion control. If weeds become a problem, they may need to be controlled by mowing.

As—Built Measurements and Record Drawings:

Field changes of dimension and detail.

C. Details not on original drawings.

- Record as—built dimensions on a daily basis and review with the Owner's Representative on a weekly basis.
 Submit complete record information on a clean set of drawings to Owner's Representative(s) upon substantial completion of work.
- As-built dimensions shall include locations of all surface features and subsurface utility systems including, but not limited to:

 A. Location, size, depths, rims, angle points, and invert elevations of buried pipes, utilities, vaults, etc.

General Construction Requirements and Utility Notes:

- 1. Contractor is responsible for all work shown on the drawings, unless otherwise noted. Provide all materials and labor necessary to complete all work shown on the drawings.
- 2. All work shall conform to the latest edition of the New Hampshire Department of Transportation (NHDOT) Standard Specifications for Road & Bridge Construction and supplemented as necessary.
- 3. Perform all work in compliance with federal, state, and local permit approvals. Copies of all permit approvals shall be maintained at the project site.
- 4. Site security and job safety are the sole responsibility of the Contractor. All construction activities shall comply
- 5. Contractor shall prepare a "Notice of Intent" and "Stormwater Pollution Prevention Plan" at least one week prior to construction in accordance with the current National Pollutant Discharge Elimination System (NPDES) requirements.

with Occupational Safety and Health Administration (OSHA) standards and local requirements.

- 6. The location of existing utilities are approximate and have not been independently verified. Contact "Dig Safe" 72 hours prior to any excavation at 1—888—344—7233 and any other utility owners for accurate utility marking. Pay for all damages which may occur by failure to locate and preserve any utilities
- 7. The Contractor shall provide a construction schedule to the Owner prior to commencing work and shall update the schedule as necessary.
- 8. At least one week prior to site clearing/demolition, request Owner's Representative to identify features to
- 9. The Engineer and Owner's Representative shall have full access to the site when the work is in preparation and progress. They may observe the work on a periodic or full—time basis.
- 10. Field—verify the location, size, inverts and types of existing pipes at all proposed points of connection prior to ordering materials. Where an existing utility is found to be in conflict with the proposed work, the location, elevation and size of the utility shall be accurately determined without delay, and the information furnished in writing to the Owner's Representative for resolution of the conflict.
- 11. All existing sewer, storm drain lines, culverts, and gas lines encountered during construction are to remain in service. Any lines damaged during construction shall be repaired by the Contractor at the Contractor's expense, except when in direct conflict with the new service or when not shown or indicated. Culverts damaged during construction shall be replaced from the damage area to the outlet.
- 12. Contractor shall remove and replace or repair all curbs, sidewalk, pavement, and other items damaged by their construction activities to, at a minimum, their original condition, to the satisfaction of the Owner.
- 13. The Contractor shall provide submittals (gradations, proctors, product data, etc.) as directed by the Owner/Engineer for all materials to be incorporated into the work.
- 14. Make all necessary construction notifications and apply for and obtain all necessary permits not provided by Owner, and pay all fees and post all bonds associated with the work indicated on the drawings.
- 15. Provide traffic control and flaggers (if required) complying with the State Department of Transportation
- 16. Construction layout is subsidiary, and is the responsibility of the Contractor.
- 17. The Contractor shall not disturb any existing property corner, monument, survey marker, or benchmark without first making provisions for its replacement or relocation. The cost of protecting existing property corners, monuments, survey markers, or benchmarks is subsidiary to the project.
- 18. Final resolution to conflicts within the specifications or any substitutions shall be determined by the Owner/Engineer.
- 19. The location and limits of on—site work and storage areas shall be reviewed/coordinated with, and acceptable to, the Owner. The Contractor shall limit activities to these areas.
- 20. Contractor shall remove and dispose of all debris, and excess excavated materials from within the construction limit of work to a suitable site provided by the Contractor, in compliance with all state and local regulations. Any excess suitable material may remain on site at the request of the Owner.
- 21. When power or telephone pole support is required, the Contractor shall provide a minimum 48—hour notification to governing utility agency.
- 22. Open trenches in the roadway must be backfilled at the end of the workday. As approved by the Owner, open trenches outside of the roadway may be left open if the Contractor provides safe barricading and lights.
- 23. All structures and pipelines to remain after project completion located adjacent to the trench excavation shall be protected and firmly supported by the Contractor until the trench is backfilled. Injury to any such structures caused by, or resulting from, the Contractor's operations shall be repaired at the Contractor's expense. All utilities requiring repair, relocation, or adjustment as a result of the project shall be coordinated through the respective utility.
- 24. All manholes, valve boxes, and other buried facilities with surface access shall be adjusted to match final grades, unless otherwise indicated.
- 25. Existing waterlines shall be removed when encountered within limits of trench for new water lines. Existing waterlines not removed as part of the work and which will not remain integral to the operation of the new system, shall be abandoned in place. This work shall be considered subsidiary to the project.
- 26. Severing existing utilities for abandonment or removal of a segment from service shall be performed in such a manner as to allow the remaining active segment to continue in its intended service. Cap active segments with appropriate fittings, joint restraint, etc., to ensure their integrity. Plug ends of abandoned pipe segments with concrete, unless special circumstances dictate plugging abandoned pipes with blind flanges, restrained mechanical joint plugs, etc. as appropriate.

Material Testing:

- 1. It is anticipated the following material testing program at a minimum will be implemented and be the responsibility of the Contractor.
- 2. Contractor shall notify Owner's Representative at least 48 hours prior to placement of materials noted below.
- 3. Contractor is responsible for supplying and installing construction materials that meet NHDOT Standard Specifications for Road & Bridge Construction, Latest Edition.

NHDOT Item	<u>Description</u>	Test Location &	Frequency
304.1	Sand	Compaction	- In Place 1/1,000 LF of waterline
		Gradation	- 1/source
304.2	Gravel	Compaction	In Place 1/Dump Station Area (Bid Item #3)
		Gradation	- 1/source
304.3	Crushed Gravel	Compaction	In Place 1/Dump Station Area (Bid Item #3)
		Gradation	- 1/source
403.11023 403.11053	Hot Bituminous Pavement	Compaction	In place 1/Dump Station Area (Bid Item #3, binder & wearing)In place 1/project on pavement trench (Bid Item #3, binder & wearing)
_	ASTM C-33 Std. Stone #67	Gradation	- 1/source
-	Chamber Bedding	Gradation	- 1/source (Bid Item #3)

Civil Sheet Index

<u>Number</u>	<u>Sheet</u>	Sheet Name	<u>Latest Issue</u>
1.	T-1	Cover Sheet	11/16/2023
2.	C0.02	General Notes	11/16/2023
3.	C1.01	Overall Water Plan	11/16/2023
4.	C1.11	Water Plan — Area A	11/16/2023
5.	C1.12	Water Plan — Area B	11/16/2023
6.	C1.13	Water Plan — Area C	11/16/2023
7.	C1.14	Water Plan — Area D	11/16/2023
8.	C1.15	Water Plan — Area E	11/16/2023
9.	C1.16	Water Plan — Area F	11/16/2023
10.	C1.17	Water Plan — Area G	11/16/2023
11.	C1.18	Water Plan — Area H	11/16/2023
12.	C1.19	Day Use Area Electrical and Water Plan	11/16/2023
13.	C1.21	Sewage Disposal System Plan — Dump Station	11/16/2023
14.	C5.11	Construction Details — Water	11/16/2023
15.	C5.21	Construction Details — Miscellaneous	11/16/2023
16.	C5.31	Construction Details — Dump Station	11/16/2023
17.	C5.41	Day Use Area Pump House	11/16/2023
18.	C5.51	Day Use Area General	11/16/2023

Electrical Sheet Index


<u>Nu</u>	<u>ımber</u> <u>S</u>	neet She	et Name	<u>Latest Issu</u>
1.	ES	−1 Existir	ng Electrical Utilities Site Plan/Removals	11/16/2023
2.	ES		sed New Electrical Site Utilities	11/16/2023
3.	ED	−1 Electri	ical Details and New Utilities on Line Diagram	11/16/2023
4.	ED	−2 Electri	ical Utility Details Sheet #2	11/16/2023
5.	ED	-3 Electri	ical Utility Details Sheet #3	11/16/2023
6.	ED	-4 Electri	ical Details Sheet #4 Power & Communications Details for Noted Facilities	11/16/2023
7.	ED		ical Details Sheet #5 Toilet Buildings #1—#6, Water Booster Station	11/16/2023
8.	ED	−6 Electri	ical Details Sheet #6 Toilet Buildings #7—#11	11/16/2023
9.	ED	-7 Electri	ical Panel Schedules	




HEB Engineers, Inc.
Post Office Box 440
2605 White Mountain Hwy.
North Conway, NH 03860
www.hebengineers.com
Office (603) 356-6936
Fax (603) 356-7715




REVISIONS ARPA - GREENFIELD SP UTILITIES UPGRADE PROJECT STATE OF NEW HAMPSHIRE DATE DESCRIPTION 973 FOREST ROAD DEPARTMENT OF ADMINISTRATIVE SERVICES GREENFIELD, NEW HAMPSHIRE DIVISION OF PUBLIC WORKS DESIGN & CONSTRUCTION DEPARTMENT OF NATURAL & CULTURAL RESOURCES JOHN O. MORTON BUILDING 7 HAZEN DRIVE BOX 483 ROOM 250 81204R GENERAL NOTES CONCORD, NEW HAMPSHIRE 03302-0483 NTRACT: C (603) 271-3516 FAX (603) 271-3515




P:Jobs)2022/2022-041G NHDPW - Greenfield State Park, Greenfield, NH/Dwg\Plan Set 3 - Construction Drawings\Sheet Files\2022-041G C1.01 Water Overall Plan.dwg, C







P:\Jobs\2022\2022-041G NHDPW - Greenfield State Park, Greenfield, NH\Dwg\Plan Set 3 - Construction Drawings\Sheet Files\2022-041G C1.01 Water Plans.dwg, C1.12, 1




P:\Jobs\2022\2022-041G NHDPW - Greenfield State Park, Greenfield, NH\Dwg\Plan Set 3 - Construction Drawings\Sheet Files\2022-041G C1.01 Water Plans.dwg, C1.13, 11




P:\Jobs\2022\2022-041G NHDPW - Greenfield State Park, Greenfield, NH\Dwg\Plan Set 3 - Construction Drawings\Sheet Files\2022-0410




P:Jobs\2022\2022-041G NHDPW - Greenfield State Park, Greenfield, NH\Dwg\Plan Set 3 - Construction Drawings\Sheet Files\2022-041G C1.01 Water Plans.dwg, C1.15, 11/10/




P:\Jobs\2022\2022-041G NHDPW - Greenfield State Park, Greenfield, NH\Dwg\Plan Set 3 - Construction Drawings\Sheet Files\2022-041G C1.01 Wa




P:\Jobs\2022\2022-041G NHDPW - Greenfield State Park, Greenfield, NH\Dwg\Plan Set 3 - Construction Drawings\Sheet Files\2022-041G C1.01 Wat







P:\Jobs\2022\2022-041G NHDPW - Greenfield State Park, Greenfield, NH\Dwg\Plan Set 3 - Construction Drawings\Sheet Files\2022-041G C1.20 Day Use Area Well Plan.dw




P:\Jobs\2022\2022-041G NHDPW - Greenfield State Park, Greenfield, NH\Dwg\Plan Set 3 - Construction Drawings\Sheet Files\202



P:Jobs/2022/2022-041G NHDPW - Greenfield State Park, Greenfield, NH/Dwg/Plan Set 3 - Construction Drawings\Sheet Files\2022-041G C5.11 Construction Details dwg, C5.11, 1



P:\Jobs\2022/2022-041G NHDPW - Greenfield State Park, Greenfield, NH\Dwg\Plan Set 3 - Construction Drawings\Sheet Files\2022-041G C5.11 Construction Details.dwg, C5.21, 11/10/2023



P:Jobs/2022/2022-041G NHDPW - Greenfield State Park, Greenfield, NH\Dwg\Plan Set 3 - Construction Drawings\Sheet Files\2022-041G C5.11 Construction Details.dwg, C5.31, 11/10/2023 7:52.28 AM, alama

2. All construction shall conform to the current New Hampshire State Building Code (International Code Council (ICC), International Building Code (IBC), 2018 Edition, with NH Amendments).

3. Details shown on any drawing are considered typical for all similar conditions unless noted otherwise.

4. The Contractor shall be responsible for any shoring or temporary bracing required to complete the work.

5. Shop drawings shall be submitted to the Engineer and approved prior to fabrication or use of material on the

6. The location of underground and overhead utilities are not shown on these drawings. Verify the location of all utilities and contact all utility companies before beginning construction. Contact DIG—SAFE at

7. The Contractor shall use the structural drawings in coordination with the other drawings and coordinate the work of the various trades. Verify all dimensions and rough openings with the architectural drawings.

8. The following criteria was used for the design of the structure:

Snow Loads
Approx. Site Elevation = 850 ft
Site Ground Snow Load, pgsite = 75 psf
Terrain Category B
Exposure Factor, Ce = 1.0
Thermal Factor, Ct = 1.2
Importance Factor, Is = 0.8
Flat Roof Snow Load, pf = 50 psf

Wood Framing Notes:

1. All wood construction shall conform to the American National Standards Institute (ANSI) and American Forest & Paper Association (AF&PA), National Design Specification for Wood Construction (NDS), 2018 edition.

2. The Contractor is required to ensure a continuous load path to the foundation for all columns and jack/king studs, unless interrupted by a transfer beam or other supporting member.

3. Unless noted otherwise, all fastening shall be in accordance with IBC 2018, Fastening Schedule, Table 2304.10.1.

4. Bolts shall meet the requirements of ASTM A307. Anchor rods shall meet the requirements of ASTM F1554 Grade 36, unless noted otherwise.

5. Built up beams, headers, or girders shall be continuous members throughout their span. Joints shall be allowed only over columns.

6. Provide mid—height blocking for all wall studs in excess of 8 feet in height.

7. All floor trusses/joists shall align with the wall stud below.

8. Wood and engineered—wood products shall bear the stamp of a recognized grading agency and have, at minimum, the following properties or classifications:

Dimensional Lumber — Spruce/Pine/Fir (SPF) No. 1/No. 2

Pressure Treated Dimensional Lumber — Southern Yellow Pine (SYP) No. 1

9. All wood panels for wall applications shall be $^{15}\!\!/_{32}$ —inch APA rated sheathing $^{32}\!\!/_{16}$, Exposure 1.

10. All wood panels for roof applications shall be $\frac{1}{2}$ —inch APA rated sheathing $\frac{4}{2}$ 0, Exposure 1

11. All sheathing construction joints shall be lapped per Manufacturer's recommendations.

12. Mechanical connectors shall be Simpson Strong—Tie or approved equivalent.

13. The Contractor is responsible for ensuring proper corrosion protection for fasteners, hangers, and other hardware from the elements and pressure treatment. Consult manufacturer for specifications.

14. All holes or cuts, in pressure treated wood, shall be properly field treated with preservative. Consult manufacturer for recommendations.

15. Nails shall have non-clipped heads and shall have the following dimensions: 8D: ϕ = 0.131" L= $2\frac{1}{2}$ " 10D: ϕ = 0.148" L= 3"

<u>Cast—in—Place Concrete Notes</u>:

12D: $\emptyset = 0.148$ " L= $3\frac{1}{4}$ " 16D: $\emptyset = 0.162$ " L= $3\frac{1}{2}$ "

1. All concrete construction shall conform to the American Concrete Institute (ACI), <u>Building Code Requirements</u> for Structural Concrete (ACI 318—14) and ACI <u>Specifications for Structural Concrete for Buildings</u> (ACI 301).

2. Unless otherwise noted, all concrete shall have a compressive strength of at least 3,000 psi at 28 days and air entrainment of 4-7%. Slump shall be 4-5 inches. A mid-range water-reducing agent may be used to improve placement, workability, and increase slump to a maximum of 7 inches. Mix shall be approved by the Engineer prior to its use on the project.

3. Calcium chloride or admixtures containing calcium chloride shall not be used in any concrete mix.

4. All reinforcing steel shall be deformed bars ASTM A615, Grade 60. Reinforcing shall be installed in accordance with ACI 318—14 and <u>Details and Detailing of Concrete Reinforcement</u> (ACI 315). Reinforcing shall be installed at the proper location and secured in place to prevent movement during placement of concrete.

5. All welded wire fabric (WWF) shall conform to ASTM A185, provided in flat sheet stock. The WWF shall be installed at the proper location and secured in place to prevent movement during placement of concrete. Lap 6 inches at all joints and tie at 3 inches on center.

6. Lap all continuous bars 40 diameters, unless noted otherwise.

7. Clear distances for protection of reinforcing shall be as follows: Footings: 3" from ground

Footings: 3 from ground Slabs—on—Grade: 3" from ground

8. No bars shall be cut or omitted in the field because of sleeves, ducts, openings, or recesses. Bars may be moved aside without changing level with approval of the Engineer.


9. Pipe sleeves and/or pvc conduits shall be spaced a minimum of 3 diameters apart.

10. Details not shown on the drawings shall be in accordance with the ACI Detailing Manual.


11. Concrete placement during cold or hot weather must follow the requirements of ACI <u>Guide to Hot Weathering</u> <u>Concreting</u> (ACI 305R) and ACI <u>Guide to Cold Weather Concreting</u> (ACI 306R).

12. Interior slab on grade to have a smooth steel trowel finish and be true to line and grade within ¼ inch in 10 feet. Exterior slabs on grade to have broom finish. Seal slabs with approved curing compound within 48

13. Anchor bolts shall be of the size and location shown on the drawings or specified by equipment manufacturers. Bolts shall conform to ASTM A307. Headed anchor bolts shall be installed using appropriate templates to maintain spacing and alignment prior to placement of concrete. Wet—setting is unacceptable.




Pump House Detail
Scale: 1" = 1'-0"




Engineers

CIVIL • STRUCTURAL • SURVEY


HEB Engineers, Inc.
Post Office Box 440
2605 White Mountain Hwy.
North Conway, NH 03860
www.hebengineers.com
Office (603) 356-6936
Fax (603) 356-7715





ARPA - GREENFIELD SP UTILITIES UPGRADE PROJECT STATE OF NEW HAMPSHIRE DATE DESCRIPTION BY DEPARTMENT OF ADMINISTRATIVE SERVICES 973 FOREST ROAD GREENFIELD, NEW HAMPSHIRE DIVISION OF PUBLIC WORKS DESIGN & CONSTRUCTION DEPARTMENT OF NATURAL & CULTURAL RESOURCES JOHN O. MORTON BUILDING 7 HAZEN DRIVE BOX 483 ROOM 250 81204R DAY USE AREA PUMP HOUSE CONCORD, NEW HAMPSHIRE 03302-0483 NTRACT: C (603) 271-3516 FAX (603) 271-3515 C5.41 AS NOTED



P:Jobs\2022/2022-041G NHDPW - Greenfield State Park, Greenfield, NH\Dwg\Plan Set 3 - Construction Drawings\Sheet Files\2022-041G C5.11 Construction Details.dwg, C5.51, 11/10/2023 9:06:15 AM, alar







The trench shall be in as direct a line as possible without reverse bends from the distribution facility to the customer service entrance. In order to minimize cable pulling forces, no more than two bends (not including riser at house or pole) exceeding a total combined change of 45 degrees shall be permitted.

- 1. Trench shall be of such depth to accommodate 24 inches minimum cover for service cables in conduit,
- In order to prevent the conduit from being pulled out of the meter box, conduit shall be installed on virgin or well tamped soil. Trench bottom shall be undisturbed or relatively smooth earth, well tamped, and free of any debris that may be detrimental to the conduit.
- Conduit in the trench should have a 4-inch-per-100-feet downward pitch toward the distribution facility, if physically possible. (This provides drainage away from the service entrance, and prevents stagnant water in
- 4. Backfill shall not contain frozen material or stones larger than 2 inches in maximum dimension. Care shall be exercised to avoid damage to conduit during backfilling. Backfill shall be compacted, and shall be completed before the Company schedules cable Installation.
- When required, coordination with telephone, cable TV, or other utilities is the Customer's responsibility.

CONDUIT - By Customer

Standard conduit shall be minimum 3-inch diameter, rigid PVC, heavy wall, sunlight resistant (6%-7% titanium dioxide by weight), Schedule 40 as per ANSI/NEMA TC2-1990.

- A 90° Schedule 40 PVC bend, 24-inch minimum radius, shall join the meter socket conduit to the conduit in the trench. See DTR 54.114.
- 2. Bends in the conduit run shall have a minimum radius of 48 inches. This requirement does not include bends used at house or pole risers where the bend radius shall be a minimum of 24 inches, with 36 inches preferred.
- 3. A 1/4-inch-diameter nylon pull rope, including 10 feet of slack, shall be installed in the conduit. Secure the pull line to a plastic conduit plug (e.g., SC 0175161 for 3-inch diameter), at each end of the conduit run. Plugged ends of the conduit shall be left accessible.

SERVICE FROM POLE - If service is from an OH system, a grounded 90° galvanized steel bend shall be installed at the pole. See DTR 12.057.

SERVICE FROM HANDHOLE/TRANSFORMER - Extend conduit to distribution facility and mate to previously installed 10-foot conduit stub. Tie pull lines, slide conduit sleeve over both ends and secure with conduit cement.


CAUTION - Customer shall not enter any Company structure because it could be energized.

LIMITATIONS - If the route chosen for the conduit requires more than two bends (not including the bend at the riser or the house) exceeding a total of a 45° change in direction, the Company may refuse to permit the conduit service and a direct-buried service would be installed.

COMPANY CONSIDERATIONS - Services in conduit shall be identified at the transformer or handhole with a brass "SVC IN CNDT" tag. To aid troubleshooting, conduit service shall be clearly designated on mapping records.

ORIGINAL 9/29/87	DIRECT-BURIED SERVICES IN CONDUIT			
APPROVED		600 VOLT AND BELOW		
814/05 -1015/1	NORTHEAST UTILITIES	DESIGN & APPLICATION STANDARD	DTR 54.113	5

23




1. Install the intermediate standoff bracket equidistant from the upper and lower brackets.

2. Whenever possible install electrical facilities nearest to the pole. > 3. Preferred location for riser placement is on field side of pole opposite the direction of traffic. Check riser path for obstructions, and coordinate with other utilities for placement of risers and any equipment. (Road side of pole opposite the direction of traffic is reserved for road crossings.)

ORIGINAL 8/16/94 APPROVED	CABLE RIS	ER STANDOFF BRACKET INSTA	LLATION	NH
7/13/11 Cup	NORTHEAST UTILITIES	CONSTRUCTION STANDARD	DTR 12.017	2

THIS WORK IS NIC 29

> CARROLE Mc. 2628




- Set meter socket plumb (by Customer). 2. Attach 2 1/2" x 2 1/2" adhesive backed signs: "WARNING, UNDERGROUND CABLE" and 3" x 5" "ELECTRIC
- SERVICE IN CONDUIT." See SPC's S-471 and S-474. Attach lettering to identify the source. See DTR's 43.061 and 43.062 NOTE 3.

-30" MINIMUM REQUIRED, THIS PROJECT

4. The Company will furnish the cable and meter. In New Hampshire, the Company will also furnish the meter socket and caution tape. Balance of the material is to be furnished by the Customer.

ORIGINAL 9/28/87 APPROVED	DIRE	CT-BURIED SERVICES IN CONDU 600 VOLT AND BELOW	İT	
9/14/05	NORTHEAST UTILITIES	DESIGN & APPLICATION STANDARD	DTR 54.114	5




 To inspect, provide access, operate elbow connectors and ventilate the transformer, the above specified clear area distances to buildings or shrubs shall be maintained. The distance from the building is to the concrete transformer pad. Property line shall be considered an obstruction, since fences, shrubs, etc. may be installed at a future date by adjacent property owners. Because of the possibility of cooling fins overhanging the pad, side clearances to be increased to 5 feet for transformers 1000 kVA and larger.

- 2. If no curb exists, or transformer is located closer than 10 feet to the traveled way, protective vehicle posts (a) shall be installed as specified in DTR 42.061.
- 3. Top of transformer pad shall be installed 3 inches above final grade. Transformer shall not be located on steep grades where access to or elbow operation is made difficult.
- Transformer shall meet the minimum distances to doors, windows, fire escapes, air intakes and walls as
- Transformer is not to be located with its doors facing the building. Refer to DTR 58.301 for specific instructions on the installation of the transformer pad.

8. Refer to DSEM Section 06.32 and DTR 58.311 (NH) for information on environmental considerations. DAD MOUNTED TRANSFORMEDS

OTHORNE:	P/	AD-MOUNTED TRANSFORMERS		
4/10/91				
APPROVED	LOCAT	ION TO BUILDINGS AND ROADWA	AYS	
7/5/10	NORTHEAST UTILITIES	CONSTRUCTION STANDARD	DTR 42.047	



➤ BELOW GROUND ENCLOSURE

1. All PVC conduit shall be UL approved, gray in color, and at least Schedule 40 electrical grade that meets NEMA TC2-1990 requirements. Rigid galvanized steel conduit may also be used. CAUTION: See NOTE 2 -Galvanized Sweep Elbows.

- > 2. All sweep elbows shall be galvanized steel type approved for electrical cables and have approved sealing compound applied to threaded coupling.
- Temporary approved conduit end caps shall be placed on the exposed ends of conduit. Necessary measures shall be taken to prevent water, sand, and other objects from entering the conduit during and after construction. After construction is complete, seal conduits using proper methods (one method is expanding polyurethane
- A suitable pulling string, capable of 200 pounds of pull, shall be installed in the conduit system. Avoid bonding the string to the conduit with the fresh PVC cement.
- 5. A sweep elbow and a 10-foot section of conduit, with a watertight end cap, shall be installed for all known future load to be fed from an enclosure. Remove all organic topsoil under enclosure and compact native material. Backfill, if necessary, with clean, well
- Watertight, URD service entrance multiple outlet connectors shall be used in the below ground enclosure.
- 8. On below ground enclosure, bring both conduits in at one end. This will allow the secondaries to be installed lengthwise in the enclosure so that working stack is available.

ORIGINAL 9/19/94 APPROVED		TYPICAL SECONDARY CABLE ENCLOSURE INSTALLATION		NH
47/11 Curp	NORTHEAST UTILITIES	CONSTRUCTION STANDARD	DTR 54.215	4

NOT REQUIRED FOR THIS PROJECT

GENERAL - Pad-mounted oil insulated equipment (such as transformers, transclosures, switches, etc) should be installed so as to be accessible, not constitute an environmental hazard or a fire hazard, and be protected from famage. In URD areas transformers installed at residential front lot lines are not subject to the re this Standard, refer to DTR 42.031.

LOCATION - The pad-mounted equipment should be installed at a location where permanent access will be assured for future operation and maintenance as well as to permit installation, replacement and removal of the equipment by means of a winch truck with the boom up. Where noise may be a problem, careful consideration should be given when selecting a location. Areas subject to flooding should be avoided, as should other environmentally sensitive areas noted in DSEM Section 06.32. The building owner's and/or tenant's fire insurance carrier may restrict the proximity of the equipment to doors, windows or combustible materials and such requirements are the responsibility of the customer subject to the requirements of Northeast Utilities. In the absence of other requirements, the equipment shall be located with the following minimum clearances from various building facilities. The distances mentioned in this section shall not supersede any local ordinance or code which requires greater clearances.

	Minimum	Distance	
<u>Item</u>	In Front of In Feet_	To Side of In Feet	Below In Fee
Door	20	10	-
Air intake	10	10	25
Window	10	3	5
Fire escape	20	20	-
Combustible wall	6	6	-
Noncombustible wall	5	3	-
Fuel tanks (above and below grade) Natural gas or propane connections	10	10	-
CT/MA	3	3	-
NH	15	15	-
Gasoline dispensing unit	20	20	-

OIL SUMP - If the surrounding grade pitches toward critical areas, it is recommended that an oil sump be provided. This should consist of 3/4-inch trap rock fill under and around the equipment pad adequate to contain the quantity of oil in the equipment to be installed at the given location.


ADDITIONAL FIRE PROTECTION - If the building owner's and/or tenant's combustible facilities adjacent to the equipment require fire protection beyond that provided by oil sump, it shall be their responsibility to provide such protection in the form of space separation, fire resistant barriers, automatic spray systems, other oil containment facilities, or other means approved by their fire insurance company.

EQUIPMENT PROTECTION - Where pad-mounted equipment would be exposed to possible damage by vehicular traffic, protective bumpers are to be installed on exposed sides. Galvanized steel pipes 4-inch minimum diameter filled with concrete, I-beams 5-inch minimum, or other suitable means of protection may be used as bumpers. Such pipes or I-beams shall extend 42-inch minimum both above and below grade. Heavier bumpers set deeper should be considered where exposed to heavy trucks. Bumpers should be 10-foot minimum from the operating side of concrete pad and on the other sides 36-inch minimum from equipment or pad, whichever projects farther. The maximum spacing between bumpers on exposed sides should be 60 inches.

EQUIPMENT LOCKS - Any equipment, with provisions for locking, that is left on site and is accessible to the general public, shall be padlocked. This includes installations that are not complete and not energized. Completed pad-mount transformer installations shall meet "TAMPERPROOF EQUIPMENT LOCK" requirements, DTR 03.401.

GRIGINAL 12/6/13	PAD-MOUNTED OIL INSULATED EQUIPMENT			
1/25/02				
Dohour	NORTHEAST UTILITIES	DESIGN & APPLICATION STANDARD	DTR 42.061	9

Primary/Secondary Cable Installation



D = 36 Inches for primary voltage cable 30 Inches for secondary cables


ELECTRICAL UTILITY STANDARD TRENCH DETAIL

NOTE: PROVIDE SAND BEDDING/SUITABLE FILL PER COMMUNICATIONS CONDUIT SPECIFICATIONS DETAIL. THIS DRAWING. NOTE: WHERE LEDGE DOES NOT PERMIT DEPTHS NOTED, CONCRETE ENCASEMENT WILL BE REQUIRED TO CONFORM TO NEC AND/OR UTILITY REQUIREMENTS, WHICH EVER IS MORE STRINGENT.

- 1. All non-metallic conduit and fittings shall be electrical grade, schedule 40 PVC, shall conform to the applicable sections of NEMA and be UL Listed. Only gray-colored conduit will be accepted. Any PVC conduit not having the proper NEMA and UL markings will not be accepted. All steel conduits shall conform to ASTM A120 and be rigid galvanized steel. All PVC conduit joints must be cemented. Steel fittings shall be sealed with compound.
- 2. All 90-degree sweeps will be made using rigid galvanized steel with a minimum radius of 24" for 3" conduit, 36" for 4" conduit and 5" conduit, and 48" for 6" conduit. All steel sweeps within 18" of surface shall be properly grounded.
- 3. A 10' horizontal section of rigid galvanized steel conduit will be required at each
- sweep for primary. 4. The conduit should cross paved areas at approximately 90 degrees.
- 5. Backfill may be made with excavated material or comparable; unless material is deemed unsuitable by the Company. Backfill shall be free of frozen lumps, rocks or stones 2" maximum in dimension, debris, and rubbish. Organic material shall not be used as backfill. Backfill shall be thoroughly compacted in six-inch layers.
- 6. A suitable pulling string, capable of 200 pounds of pull, must be installed in the conduit before the Company is notified to install cable. The string should be blown into the conduit after the run is assembled to avoid bonding the string to the
- 7. Routing of the conduit and inspection prior to backfill will be provided by the Company. Installation of the conduit will be done by the contractor. A Company Representative must be notified two business days prior to backfilling the trench. If a cable cannot be successfully pulled through the completed conduit system due to a construction error, it will be the contractor's responsibility to locate and repair the involved conduit. The contractor will be responsible for all resulting
- 8. Normal conduit sizes for the Company are 3" for single phase primary and secondary voltage cables, 4" for three phase secondary, and 5" for three phase primary.
- 9. All conduit installations must conform to the National Electrical Safety Code, state and local codes and ordinances, and where applicable, the National Electrical Code.
- 10. Other utilities shall maintain a minimum distance of 12" in all directions from the Company conduit.

NOTE: CONDUIT ROUTINGS (#4 ABOVE) INDICATED DO NOT ALL CONFORM TO NOTE #4 ABOVE.

THIS HAS BEEN DONE TO MINIMIZE PULL BOXES AND CONDUIT/CABLE LENGTHS AND HAS BEEN SUBMITTED TO THE UTILITY(IES) FOR THEIR APPROVAL AND VERBALLY ACCEPTED. NOTE: #5 ABOVE REFERS TO ALL PRIMARY POWER CONDUITS AND ALL SECONDARY CONDUITS FROM TRANSFORMERS TO UTILITY METERS.



- The meter mounting device shall be installed approximately 5 feet above the final grade except where specifically approved otherwise by the Company. It shall be plumb level and attached to the finished exterior of the building
- with rust-resistant screws extending through the finish and into the sheathing. Furnish, install, and connect NEC approved ground electrodes. 3. Furnish and install service entrance cable from meter mounting device to switch box.
- ➤ 4. Furnish and install Schedule 40 PVC conduit except as noted. Install caution tape 12 inches below grade. Provide a rigid steel elbow.
- 5. Equipment and installation must comply with the latest edition of the National Electrical Code (NEC) and all local codes. Expansion joint in conduit shall comply with NEC 300-7(b).
- For services in excess of 200 feet servicing homes larger than 3,000 square feet, parallel 3-inch conduits shall be installed to a below-ground service enclosure located no more than 10 feet from the meter mounting device. A single 3-inch conduit from the service enclosure to the meter mounting device is sufficient, see DTR 54.215.
- ➤ 7. For services with any elevation change, PSNH may require a service enclosure located no more than ten feet from meter mounting device. COMPANY RESPONSIBILITY
- Furnish meter mounting device (permanent service only). Furnish caution tape. Furnish and install cable and meter.
- 3. Attach 2 1/2" x 2 1/2" adhesive-backed signs: "WARNING, UNDERGROUND CABLE" and 3" x 5" "ELECTRIC
- SERVICE IN CONDUIT'. See MAT L-013. 4. Attach lettering to identify the source. See DTR Section 43.

ORIGINAL 10/21/08 APPROVED	TEMPORARY	//PERMANENT UNDERGROUND S 400 AMP & BELOW	ERVICE	NH
477/11 Cmp	NORTHEAST UTILITIES	CONSTRUCTION STANDARD	DTR 54.116	3

NHDPW

11-16-2023

81204R

ED-2

ONTRACT: C

31 22 REVISIONS STATE OF NEW HAMPSHIRE GREENFIELD STATE PARK IMPROVEMENTS DESCRIPTION 973 FOREST ROAD GREENFIELD, NEW HAMPSHIRE

DEPARTMENT OF ADMINISTRATIVE SERVICES DIVISION OF PUBLIC WORKS DESIGN & CONSTRUCTION JOHN O. MORTON BUILDING 7 HAZEN DRIVE BOX 483 ROOM 250 Electrical Utility Details Sheet #2 CONCORD, NEW HAMPSHIRE 03302-0483 (603) 271-3516 FAX (603) 271-3515


CIVIL . STRUCTURAL . SURVEY


HEB Engineers, Inc. Post Office Box 440 2605 White Mountain Hwy. North Conway, NH 03860 www.hebengineers.com Office (603) 356-6936

Fax (603) 356-7715

ELECTRICAL DESIGN BY: Lee F. Carroll, PE 603-466-5065 lcarroll@ne.rr.com

Electrical Consultants Madison Ave P.O. Box 35 Gorham, NH 03581-0357 Copyright © 2023 by Lee F. Carroll, PE Electrical Consultants. All rights reserved





TRANSFORMER SLAB DETAILS

(53) 101


Preparation of Slab:

- Remove all organic topsoil under foundation and compact native material. Backfill, if necessary, with clean well compacted gravel.
- 2. Concrete shall have a minimum compressive strength of 3,500 PSI at 28 days.
- 3. All reinforcing bars shall meet A.S.T.M. #615 grade 60 specifications.
- 4. All reinforcing shall be tied as one unit.
- 5. Minimum concrete cover over reinforcing steel shall be 3 inches.
- 6. Top of slab should be no more than 6 inches above ground level.
- 7. Chamfer all exposed concrete edges 1 inch.
- Top of slab shall have a wood float finish.

lotes:

- Elbows should be cut 4 inches above bottom of concrete pad, surrounded with sand, and have a protective cap bushing on them.
- A 1 inch PVC conduit sleeve shall be incorporated into concrete slab to allow ground grid leads to enter pit openings as shown on details.
- 3 Installation of Padmounted Equipment Grounding Grid is outlined in Construction Standard DTR 56.223

May .	D. Mille Commission		ISŞUE	D
À	Public Service	CONSTRUCTION REQUIREMENT	Original	2/
N.	of New Hampshire		Rev.	1/



EQUIPMENT PROTECTION/BOLLARDS
WHERE PAD-MOUNTED EQUIPMENT, SECTOR CABINETS, ETC. COULD BE EXPOSED TO POSSIBLE DAMAGE

BY VEHICULAR TRAFFIC, THE CONTRACTOR SHALL PROVIDE AND INSTALL PROTECTIVE BUMPERS/BOLLARDS

ON EXPOSED SIDES. GALVANIZED STEEL PIPES 10" MINIMUM DIAMETER FILLED WITH CONCRETE. SUCH

PIPES SHALL EXTEND 42" MINIMUM ABOVE GRADE (BUMPERS SHALL BE SET IN CYLINDRICAL CONCRETE FOUNDATIONS MINIMUM OF 24" IN DIAMETER AND A MINIMUM OF 60" BELOW GRADE). BUMPERS SHOULD BE 10' MINIMUM FROM THE OPERATING SIDE OF CONCRETE PAD AND ON THE OTHER SIDES 36"

MINIMUM FROM EQUIPMENT OR PAD, WHICHEVER PROJECTS FARTHER. THE MAXIMUM SPACING BETWEEN

BUMPERS ON EXPOSED SIDES SHOULD BE 60". BUMPERS SHALL HAVE A PVC COVERING, COLOR PER

BUMPERS/BOLLARDS FOR EACH TRANSFORMER, SECTOR CABINET, AND THE DISTRIBUTION ENCLOSURE

UTILITY, EXTENDING THE LENGTH OF THE UNIT AND COVERING THE TOP.

FOR TB #6 AND THE BOOSTER PUMPS.


FOR BIDDING PURPOSES ON THIS PROJECT THE CONTRACTOR SHALL INCLUDE THREE

CUSTOMER RESPONSIBILITY

The ground grid shall be supported.

The ground grid shall be supplied and installed by the customer and is to be buried at least 12 inches below grade. Eight feet of extra wire for each ground grid leg shall be left exposed in the cable compartment to allow for the connection to the transformer. The two 8-foot ground rods may be either galvanized steel or copperweld and they shall be connected to the grid with NEC approved connectors.


				A
PAD-MO	DUNT EQUIPMENT GROUNDING O	RID	4	NED
				-
NORTHEAST LITH ITIES	CONSTRUCTION STANDARD	DTD	E6 222	Α
NONTHEAST OTHER IES	CONSTRUCTION STANDARD	חום	50.225	4
	PAD-M	PAD-MOUNT EQUIPMENT GROUNDING ON NORTHEAST UTILITIES CONSTRUCTION STANDARD	PAD-MOUNT EQUIPMENT GROUNDING GRID	PAD-MOUNT EQUIPMENT GROUNDING GRID



SINGLE PHASE TRANSFORMER

NOTE: PRECAST UNITS MAY BE USED SUBJECT TO THEIR APPROVAL BY THE UTILITY.

3/8" : 1"



Notes

(53) 102

- To calculate dimension of the stone-filled moat:
- Convert gallons of oil in the transformer to cubic feet: Divide gallons by 7.48 to get cubic feet of oil.
 Divide this number by 0.35 to determine the volume of stone-filled most required.
- From the table below select the width necessary to contain the oil.
- In environmentally sensitive areas, seal all conduits. See DTR 44.353.
 Refer to DSEM Section 06.32 for when an oil detention most should be used.

Volume in Cubic Feet of 24" Deep Stone-Filled Moat

	Sla	b Dimensions in Inch	98
Width of Moat (Feet)	66 x 50	80 x 92	90 x 96
1	47	65	70
2	109	147	156
3	188	244	258

OHIGINAL B/E/08	OIL DETENTI	ON FOR PAD-MOUNTED TRANSF	ORMERS «	NH
APPROVED				V
7,9110 Cwp.	NORTHEAST UTILITIES	CONSTRUCTION STANDARD	DTR 58.311	2

FOR ALL TRANSFORMERS, THIS PROJECT

Overhead Design Section 06.32

Environmental Considerations

06.321

ENVIRONMENTAL CONSIDERATIONS

Permits – Prior to the start of construction, all necessary environmental permits, whether federal, state and/or local should be secured. It should be noted that jurisdiction over utility company activities varies within each state, and exemptions may exist for some utility maintenance activities. Where environmental considerations exist, our policy is typically to notify and consult with local agencies regarding significant maintenance activities, even in cases where we do not have a legal requirement to do so.

Work in areas where the following issues exist will usually draw public attention, and may require permits:

- Coastal zone
 Inland wetlands
- Tidal wetlands
- Water bodies (rivers, lakes, streams, ponds, etc.)
- Scenic roads (these are state designated)
- Historic districts
 Tree trimming/removal
- Cultural/archaeological sites.

Specific issues for each project should be addressed with the appropriate Regional/Zone Environmental

Placement of Oil-filled Distribution Equipment – Oil-filled equipment must be placed in the best possible environmental location, considering the potential for oil spills and the effect on the environment, and avoiding sensitive sites whenever feasible. Sensitive sites include hospitals, schools, food preparation centers, agricultural areas, inland wetlands and water bodies, etc.

For pad-mounted transformers, refer to DTR Section 42 for more information.

The locating of oil-filled equipment should consider: Waterways (e.g., adjacent to a stream, catch basin); public health (e.g., school yard); vandalism potential (e.g., location); and damage potential (e.g., sharp curve, large trees, etc.). Where the placement of the oil-filled equipment is questionable, consult the appropriate Regional/Zone Environmental Coordinator.

The following guidelines are recommended, where possible, to avoid placement of oil-filled equipment in the vicinity of water resources:

- 200 feet from rivers/perennial streams/bodies of water/inland and tidal wetlands


400 feet from public drinking water supply.


Asbestos Precautions – Projects involving removal and disposal of asbestos—containing duct or cable require that sufficient precautions be taken to prevent the asbestos from becoming friable (crumbling). This might be a concern on projects requiring duct or riser repair/replacement or cable replacements (e.g., Orangeberg, Transite, Parkway, etc.). For further information refer to the "Environmental Coordinators Manual," or contact the Environmental, Health and Safety Department.

Northeast Utilities Distribution System Engineering Manual May 2001

32

Single Phase Section Cabinet Foundation





REINFORCING SCHEDULE (#6 BAR)

Type Qty Length Diagram

U1 4 104" 28 28 28

Total Foundation Weight, 2,850 lbs.

NOTE: PRECAST UNITS MAY BE USED SUBJECT TO THEIR APPROVAL BY THE UTILITY.

EVERSOURCE INTERNAL REFERENCE 53.125

Refer to Installation Requirements for Padmounted Transformer and Sector Cabinets for additional details.



HEB Engineers, Inc.
Post Office Box 440
2605 White Mountain Hwy.
North Conway, NH 03860
www.hebengineers.com
Office (603) 356-6936
Fax (603) 356-7715

ELECTRICAL DESIGN BY:
Lee F. Carroll, PE
Electrical Consultants


1 Madison Ave P.O. Box 357
Gorham, NH 03581-0357
603-466-5065
Icarroll@ne.rr.com


Gorham, NH 03581-0357
603-466-5065
Icarroll@ne.rr.com

Copyright © 2023 by Lee F. Carroll, PE;
Electrical Consultants. All rights reserved.
No reproduction without permission.



STATE OF NEW HAMPSHIRE	REVISIONS	GI	REENFIELD STATE P.	ARK IMPROVEMENT	S
DEPARTMENT OF ADMINISTRATIVE SERVICES DIVISION OF PUBLIC WORKS DESIGN & CONSTRUCTION	DESCRIPTION BY	- - -	973 FORE GREENFIELD, N	ST ROAD EW HAMPSHIRE	~
JOHN O. MORTON BUILDING 7 HAZEN DRIVE BOX 483 ROOM 250 CONCORD, NEW HAMPSHIRE 03302-0483 (603) 271-3516 FAX (603) 271-3515		Elect	trical Details Sh	eet #3	PROJECT No. 81204R CONTRACT: C
ENGINEER/ARCHITECT: DESIGNED BY: APPROVED BY: CHECKED BY: Lee F. Carroll, PE		DRAWN BY:	SCALE: 1"=200'	DATE: 11-16-2023	ED-3 SHEET:






DISCONTINUED CONDUIT IN PLACE, REMOVE RISER AT EXISTING UTILITY POLE TO MINIMUM


OF 6" BELOW FINISHED GRADE. COORDINATE OUTAGE FOR CUT OVER OF SERVICE WITH

PROJECT MANAGER AND OWNER'S REPRESENTATIVE. BOND NEW GROUND ELECTRODE

CONDUCTOR TO ANY METAL PIPING IN BUILDING.


- PAD MOUNTED TRANSFORMER 2/S6T11 BY UTILITY NEW UTILITY METER WITH 150A MAIN SERVICE DISCONNECT. PEDESTAL BY CONTRACTOR TO UTILITY STANDARDS FIELD ROUTE TO EXISTING 60A MAIN DISCONNECT EXPANSION -TO UTILITY -UE -FITTING 2-4/0, 1-2/0 NEUTRAL (BY UTILITY)-3" CONDUIT (BY CONTRACTOR) GROUND PER-- NEW GROUND ELECTRODE CONDUCTOR, UTILITY STANDARDS #2 AWG TO 3-3/4"ø X 10ft LONG 3-2/0, 1-#4Gr; 3"C COPPERWELD GROUND RODS IN TRIANGULAR (BY CONTRACTOR) PATTERN, 10ft ON CENTER. WITH **EXOTHERMIC CONNECTIONS.** REAR OF TOILET BUILDING #2 PIPE CHASE AREA EXISTING PANEL QOB-16L100DS WITH 2-20A, 1P CIRCUITS (TO REMAIN) EXISTING 60A FUSED MAIN -FIELD ROUTE TO EXISTING 60A MAIN (TO REMAIN) WOOD WALKWAY CONTRACTOR TO COORDINATE WITH RAILINGS OWNER'S REPRESENTATIVE FOR RISER LOCATION AND REPOSITIONING OF ANY SIGNAGE REQUIRED FRONT OF TOILET BUILDING #2 - EXISTING CONCRETE PAD TO PEDESTAL METER/MAIN DISCONNECT SKETCH OF BUILDING TOILET BUILDING #2 ELECTRIC SERVICE NOTE: REMOVE EXISTING SERVICE CONDUCTORS THAT ARE IN CONDUIT. REMOVE EXISTING RGS CONDUIT TO EXISTING MAIN DISCONNECT TO BELOW FLOOR LEVEL. ABANDON DISCONTINUED CONDUIT IN PLACE, REMOVE RISER AT EXISTING UTILITY POLE TO MINIMUM OF 6" BELOW FINISHED GRADE. COORDINATE OUTAGE FOR CUT OVER OF SERVICE WITH PROJECT MANAGER AND OWNER'S REPRESENTATIVE. BOND NEW GROUND ELECTRODE CONDUCTOR TO ANY METAL PIPING IN BUILDING. REPAIR/REPLACE CONCRETE PAD, WOOD WALKWAY, AND ANY OTHER BUILDING DAMAGE REQUIRED FOR NEW INSTALLATION.






OF 6" BELOW FINISHED GRADE. COORDINATE OUTAGE FOR CUT OVER OF SERVICE WITH

PROJECT MANAGER AND OWNER'S REPRESENTATIVE. BOND NEW GROUND ELECTRODE





NOTE: REMOVE EXISTING SERVICE CONDUCTORS THAT ARE IN CONDUIT. REMOVE EXISTING RGS CONDUIT TO EXISTING MAIN DISCONNECT TO BELOW FLOOR LEVEL. ABANDON DISCONTINUED CONDUIT IN PLACE, REMOVE RISER AT EXISTING UTILITY POLE TO MINIMUM OF 6" BELOW FINISHED GRADE. COORDINATE OUTAGE FOR CUT OVER OF SERVICE WITH PROJECT MANAGER AND OWNER'S REPRESENTATIVE. BOND NEW GROUND ELECTRODE CONDUCTOR TO ANY METAL PIPING IN BUILDING. CONFIRM PROPER PHASE ROTATION OF WATER BOOSTER PUMPS AFTER CUT-OVER.




HEB Engineers, Inc. Post Office Box 440 2605 White Mountain Hwy. North Conway, NH 03860 www.hebengineers.com Office (603) 356-6936 Fax (603) 356-7715


CONDUCTOR TO ANY METAL PIPING IN BUILDING.


ELECTRICAL DESIGN BY: Lee F. Carroll, PE Electrical Consultants Madison Ave P.O. Box 357 Gorham, NH 03581-0357 603-466-5065 lcarroll@ne.rr.com


OF SEA LEE CARROLE p #0. 2628 0/0 Copyright © 2023 by Lee F. Carroll, PE; Electrical Consultants. All rights reserved. No reproduction without permission.

СТ	YATE OF N	EW HAMPSI	TIRE		REVISIONS		CRE	ENFIELD STATE PA	ARK IMPROVEMEN'	TC
				DATE	DESCRIPTION	BY	l divi			10
DEPARTME	NT OF AD	MINISTRATI	VE SERVICES					973 FORE		
DIVISION OF	PUBLIC WOR	KS DESIGN &	CONSTRUCTION					GREENFIELD, NI NHD		
	M O MHOL	ORTON BUILDING						11112		
7 +		BOX 483 ROO	M 250				Electr	ical Details Sh	eet #5	PROJECT No. 81204R
(CONCORD, NEW HA	AMPSHIRE 03302-0	483				Toile	et Buildings #1	l-#6,	CONTRACT: C
((603) 271-3516	FAX (603) 271-3	3515				Wat	er Booster Sta	tion	CONTINACT. C
ENGINEER/ARCHITECT:	DESIGNED BY:	APPROVED BY:	CHECKED BY:				DRAWN BY:	SCALE:	DATE:	ED-5
Lee F. Carroll, PE	LFC	LFC	LFC				IGT	NTS	11-16-2023	SHFFT.











SKETCH OF BUILDING

TOILET BUILDING #10/ DAY USE GATE HOUSE ELECTRIC SERVICE

NOTE: REMOVE EXISTING SERVICE CONDUCTORS THAT ARE IN CONDUIT. REMOVE EXISTING RGS CONDUIT TO EXISTING MAIN DISCONNECT TO BELOW FLOOR LEVEL. ABANDON DISCONTINUED CONDUIT IN PLACE, REMOVE RISER AT EXISTING UTILITY POLE TO MINIMUM OF 6" BELOW FINISHED GRADE. COORDINATE OUTAGE FOR CUT OVER OF SERVICE WITH PROJECT MANAGER AND OWNER'S REPRESENTATIVE. BOND NEW GROUND ELECTRODE CONDUCTOR TO ANY METAL PIPING IN BUILDING.





1 REQUIRED AT SHOWER BUILDING, ADMINISTRATION BUILDING, AND AT EXISTING MAIN PARK WELL HOUSE.



HEB Engineers, Inc. Post Office Box 440 2605 White Mountain Hwy. North Conway, NH 03860 www.hebengineers.com Office (603) 356-6936 Fax (603) 356-7715

ELECTRICAL DESIGN BY: Lee F. Carroll, PE Electrical Consultants Madison Ave P.O. Box 357 Gorham, NH 03581-0357 603-466-5065 lcarroll@ne.rr.com

CARROLL 0 No. 2628 0/0-Copyright © 2023 by Lee F. Carroll, PE; Electrical Consultants. All rights reserved. No reproduction without permission.

STATE OF NEW HAMPSHIRE		REVISIONS		GREENFIELD STATE PARK IMPROVEMENTS						
	DATE	DESCRIPTION	BY	973 FOREST ROAD						
DEPARTMENT OF ADMINISTRATIVE SERVICES										
DIVISION OF PUBLIC WORKS DESIGN & CONSTRUCTION				GREENFIELD, NEW HAMPSHIRE NHDPW						
JOHN O. MORTON BUILDING					NII	PW				
7 HAZEN DRIVE BOX 483 ROOM 250				PROJECT No.						
CONCORD, NEW HAMPSHIRE 03302-0483					Electrical Details Sheet #6 8120 Toilet Buildings #7-#11 CONTRACT:					
(603) 271-3516 FAX (603) 271-3515]	t buildings #1	# 1 1	CONTRACT: C			
NGINEER/ARCHITECT: DESIGNED BY: APPROVED BY: CHECKED BY:				DRAWN BY:	SCALE:	DATE:	ED-6			
Lee F. Carroll, PE LFC LFC LFC				IGT	NTS	11-16-2023	SHEET:			

PANEL TB-6/BOOSTER PUMP DIAGRAM

2:25222			ĄĘ					AWG	KVA	LOAD	DIDECTORY					
DIRECTORY	Α	В	AWG SIZE	CKT #	POLES	BRKR	1) - \$)	BRKR	POLES	CKT #	SIZE	Α	В	DIRECTORY
* SPD				3	2	**				100	2	2 4	#2			FEEDER TO BOOSTER PUMP
* FEEDER TO TB-#6			4/0	5	2	150	<u>-</u> _	╁┼		20	1	6				GFI BREAKER — SPARE
			'	7			$\vdash \frown$	++		20	1	8			,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,	GFI BREAKER — SPARE
GFI BREAKER - SPARE	,,,,,,,,,,,,,			9	1	20	H	† †		20	1	10		,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,		GFI BREAKER — SPARE
SPACE		,,,,,,,,,,,,,	ļ	11			$\vdash \subset \vdash$	+ +		20	1	12				SPARE
SPACE				13			H	+ +		20	1	14				SPARE
SPACE				15			$\vdash \frown$	++		20	1	16				SPARE
SPACE				17			$\vdash \frown$	+ +				18				SPACE
SPACE				19			$\vdash \frown$	++				20				SPACE
SPACE				21			$\vdash \frown$	┿┼				22				SPACE
SPACE				23			$\vdash \frown$	++				24				SPACE
SPACE				25			$\vdash \smallfrown$	+				26				SPACE
SPACE				27			$\vdash \frown$	╁╅				28				SPACE
SPACE				29			├^-	┿┼				30				SPACE
SPACE				31			<u> </u>	+				32				SPACE
SPACE				33			<u> </u>	+				34				SPACE
SPACE				35			$\vdash \frown$	+				36				SPACE
SPACE	***************************************			37				+				38				SPACE
SPACE			1	39				$\downarrow \downarrow$				40				SPACE
SPACE	<i></i>			41				↓ '				42				SPACE
SUB-TOTAL	•								TRAL E						••••••	SUB-TOTAL (BASE END ONLY)
VOLTAGE: 240/120 VOLT, 1 PH/				N	OTE:							PANEL:				
MAIN BREAKER: 200A				_												
MOUNTING: SURFACE				\perp	OTAL							LOCATION:				
SC RATING: 22KA																DISTRIBUTION ENCLOSURE
NOTES: * PROVIDE WITH HANDLE																FEEDER: 3-4/0, 1-#2G; 3"C
** PER SPD MANUFAC ARRESTORS SEPARA	JRGE															

PANEL TB-10 DIAGRAM

KVA LOAD AWG							A B	$\overline{}$			A	wg	KVA	LOAD		
DIRECTORY	Α	В		CKT #	POLES	BRKR) -)	BRKI	R POLE	ES CKT		IZE	Α	В	DIRECTORY
SPD				1			<u> </u>		20	1	2					GFI BREAKER- EXISTING CIRCUIT
SPD			1	3	2	**	$\vdash \land \vdash$	 	20	1	4					GFI BREAKER- EXISTING CIRCUIT
GFI BREAKER- EXISTING CIRCUIT				5	1	20	 - ^-		20	1	6		ĺ			EXISTING CIRCUIT
EXISTING CIRCUIT				7	1	20	$\vdash \smallfrown$	 	20	1	8					EXISTING CIRCUIT
FEEDER TO DAY USE GATE			3/0	9	2	100	$\vdash \uparrow \vdash$	+	<u>20</u>	1	10					SPARE
TEEDER TO DAT OSE GATE			3/0	11	11				<u> </u>	1	12					GFI BREAKER — SPARE
GFI BREAKER - SPARE				13	1	20	$\vdash \frown$	 -	<u> </u>	1	14					GFI BREAKER — SPARE
GFI BREAKER - SPARE				15	1	20	$\vdash \frown$	 	<u> </u>	1	16					GFI BREAKER — SPARE
SPACE				17					-		18					SPACE
SPACE				19			$\vdash \frown$	 	\vdash		20					SPACE
SPACE				21			$\vdash \frown$	+	\vdash		22					SPACE
SPACE				23			$\vdash \frown$	 	-		24					SPACE
SPACE				25			$\vdash \frown$		$\neg \Box$		26					SPACE
SPACE				27			$\vdash \frown$	28								SPACE
SPACE				29			$\vdash \frown$		\neg		30					SPACE
SPACE				31			$\vdash \smallfrown$	 	$\neg \Box$		32					SPACE
SPACE				33			$\vdash \frown$		$\neg \Box$		34					SPACE
SPACE				35			$\vdash \smallfrown$	 	$\neg \Box$		36					SPACE
SPACE				37			$\vdash \frown$		$\neg \Box$		38					SPACE
SPACE			1	39			$\vdash \frown$	 	$\neg \Box$		40					SPACE
SPACE				41			$\vdash \frown$		$\neg \Box$		42					SPACE
SUB-TOTAL							(NEUTRA GROUNE								SUB-TOTAL (BASE END ONLY)
VOLTAGE: 240/120 VOLT, 1 PH/ MAIN BREAKER: 200A		NOTE								PANEL: TB-10						
	MOUNTING: SURFACE															LOCATION:
SC RATING: 22KAIC								TOTAL KVA:								TOILET BUILDING #10
NOTES: * PROVIDE WITH HANDLE	LOCKS							1017	_ 1\ 7/ 1.							FEEDER: 3-4/0, 1-#2G; 3"C
** PER SPD MANUFACTURER RECOMMENDATION. PROVIDE SURGE ARRESTORS SEPARATE FROM PANEL																1

PANEL MR DIAGRAM

	,	A B				AWG	KVA	LOAD	DIDECTORY						
DIRECTORY	Α	В	AWG SIZE	CKT #	POLES	BRKR) -)	BRKR	POLES	CKT #	SIZE	Α	В	DIRECTORY
SPD				1 3	2	**			50	2	2				EXISTING CIRCUIT
EXISTING CIRCUIT				5 7	2	30			30	2	6 8				EXISTING CIRCUIT
EXISTING CIRCUIT				9 11	2	30			30	2	10 12				EXISTING CIRCUIT
EXISTING CIRCUIT				13	1	20	$\vdash \frown$	+-	20	1	14				EXISTING CIRCUIT
EXISTING CIRCUIT				15	1	20	$\vdash \frown$	+	20	1	16				EXISTING CIRCUIT
EXISTING CIRCUIT				17	1	20	$\vdash \frown$	+-	20	1	18				EXISTING CIRCUIT
EXISTING CIRCUIT				19	1	20	$\vdash \smallfrown$	+-	20	1	20				EXISTING CIRCUIT
EXISTING CIRCUIT				21	1	20	$\vdash \frown$	+-	20	1	22				EXISTING CIRCUIT
EXISTING CIRCUIT				23	1	20	$\vdash \frown$	+-	20	1	24				EXISTING CIRCUIT
EXISTING CIRCUIT				25	1	20	$\vdash \frown$	+-	20	1	26				EXISTING CIRCUIT
SPARE				27	1	20	$\vdash \smallfrown$	+-	20	1	28				SPARE
SPARE				29	1	20	$\vdash \frown$	+-	20	1	30				SPARE
SPACE				31			$\vdash \smallfrown$	+-			32				SPACE
SPACE				33			$\vdash \frown$	+-			34				SPACE
SPACE				35			$\vdash \frown$	+			36				SPACE
SPACE				37			$\vdash \frown$	+-			38				SPACE
SPACE				39			$\vdash \frown$	+-			40				SPACE
SPACE				41			$\vdash \frown$	-			42				SPACE
SUB-TOTAL								NEUTRAL GROUND E							SUB-TOTAL (BASE END ONLY)
VOLTAGE: 240/120 VOLT, 1 PH/				NOTE:					1		PANEL:				
MAIN BREAKER: 200A					1							MR			
MOUNTING: SURFACE					┨							LOCATION:			
SC RATING: 22KAIC	C RATING: 22KAIC													MANAGER'S RESIDENCE	
NOTES: * PROVIDE WITH HANDLE	LOCKS							TOTAL							FEEDER: 3-4/0, 1-#2G; 3"C
** PER SPD MANUFAC ARRESTORS SEPARA	JRGE									, , , , , , , , , , , , , , , , , , , ,					

PANEL MF DIAGRAM


		I	A В						1/2 //4	LOAD	T					
DIRECTORY	KVA A	B	AWG	CKT #	POLES	BRKR		\$\\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\	BRK	R POLI	FS CK	KT #	AWG SIZE	A KVA	LOAD B	DIRECTORY
SPD			**	1 3	2	**			20	2		2 4				EXISTING CIRCUIT
EXISTING CIRCUIT				5 7	2	20			20	2		6 8				EXISTING CIRCUIT
EXISTING CIRCUIT				9	2	20			<u>20</u> 20	1		10 12				EXISTING CIRCUIT EXISTING CIRCUIT
EXISTING CIRCUIT				13	1	20			$\frac{20}{20}$	1		14				EXISTING CIRCUIT
EXISTING CIRCUIT				15	1	20		 	20	1	1	16				EXISTING CIRCUIT
EXISTING CIRCUIT				17	1	$\vdash \frown$	+	<u></u>	1	1	18				EXISTING CIRCUIT	
EXISTING CIRCUIT				19	1	20	$\vdash \frown$	 	<u> </u>	1		20				EXISTING CIRCUIT
SPARE				21 23	2	50			30	2		22 24				SPARE
SPARE				25	1	20	$\vdash \smallfrown$	+		1	- 2	26				SPARE
SPARE				27	1	20	$\vdash \smallfrown$	 	20	1	2	28				SPARE
SPACE				29			$\vdash \smallfrown$	+	$\dashv \Box$			30				SPACE
SPACE				31			$\vdash \frown$	┼┼-^	\dashv			32				SPACE
SPACE				33			$\vdash \frown$	+	\dashv			34				SPACE
SPACE				35			$\vdash \frown$	+	\dashv			36				SPACE
SPACE				37			$\vdash \frown$	+	\dashv			38				SPACE
SPACE				39			$\vdash \frown$	 	\vdash		4	40				SPACE
SPACE				41			$\vdash \frown$		\Box		4	42				SPACE
SUB-TOTAL								NEUTRA GROUNE								SUB-TOTAL (BASE END ONLY)
VOLTAGE: 240/120 VOLT, 1 PH/ MAIN BREAKER: 200A	/OLTAGE: 240/120 VOLT, 1 PHASE, 60HZ															PANEL:
MOUNTING: SURFACE																LOCATION:
SC RATING: 22KAIC								TOTAL KVA:							MAINTENANCE FACILITY	
NOTES: * PROVIDE WITH HANDLE	LOCKS															FEEDER: 3-4/0, 1-#2G; 3"C
** PER SPD MANUFAC	** PER SPD MANUFACTURER RECOMMENDATION. PROVIDE SURGE ARRESTORS SEPARATE FROM PANEL															, , , , , , , , , , , , , , , , , , , ,



HEB Engineers, Inc. Post Office Box 440 2605 White Mountain Hwy. North Conway, NH 03860 www.hebengineers.com Office (603) 356-6936 Copyright © 2023 by Lee F. Carroll, PE; Electrical Consultants. All rights reserved. No reproduction without permission. Fax (603) 356-7715

ELECTRICAL DESIGN BY: Lee F. Carroll, PE Electrical Consultants

1 Madison Ave P.O. Box 357
Gorham, NH 03581-0357
603-466-5065
Icarroll@ne.rr.com



STATE OF NEW HAMPSHIRE DEPARTMENT OF ADMINISTRATIVE SERVICE DIVISION OF PUBLIC WORKS DESIGN & CONSTRUCTION	REVISIONS DESCRIPTION	BY	GREENFIELD STATE PARK IMPROVEMENTS 973 FOREST ROAD GREENFIELD, NEW HAMPSHIRE NHDPW					
JOHN O. MORTON BUILDING 7 HAZEN DRIVE BOX 483 ROOM 250 CONCORD, NEW HAMPSHIRE 03302-0483 (603) 271-3516 FAX (603) 271-3515			Elect	rical Panel Sch	nedules	PROJECT No. 81204R CONTRACT: C		
ENGINEER/ARCHITECT: DESIGNED BY: APPROVED BY: CHECKED BY:			drawn by: IGT	SCALE: NTS	DATE: 11-16-2023	ED-7		